Cemseal E100SL

Solventless Epoxy Floor Coating System



The Product

Cemseal E100SL is a 98% solids low odour epoxy coating designed for using as a floor or deck coating. It makes the industrial floors dust-free, easily cleanable, joint-less and good abrasion resistance. Its finishing is glossy and available in a wide range of attractive colours.

Uses

- » New / old factory floors
- » Warehouse floor
- » Re-surfacing of factory floors
- » Food processing plants
- » Laboratories
- » Primary used in floor surfaces subjected to light traffic exposure and mechanical abuse
- » Other industrial sectors where a clean working environment is required

Advantages

- » Good resistance against light and foot traffic
- » Seamless and monolithic application
- » Economical to use due to its easiness and time saving
- » Good workability for easy and fast application
- » Good chemical resistance to wide range of chemicals (Subjected to approve by Cemseal Technical advice)
- » Prepackaged for accurate on-site mixing

Technical & Physical Data

Colour Component A : Liquid / Standard colour chart

Component B : Liquid / Clear

Component A + B : See separate colour chart

Packaging Component A + B : 6 kg / set

Coverage 30 m² / coat / set

Pot Life at 25'C 20 minutes

Curing Time at 25'C Foot Traffic : 24 hours Fully Cured : After 7 days

Thinner / Cleaner Xylene or M.E.K. Solvent

Shelf Life 12 months of kept in a cool dry sheltered place

Cemseal Industries Sdn Bhd

(Co. No.884153-T) 9 & 11, Jalan Besi, Taman Sri Putri, 81300 Skudai, Johor, West Malaysia

T +607-558 3320 **F** +607-556 9127

E info@cemseal.com.my

Method of Statement

Substrate Preparation

NEW CONCRETE: The surface must be firm, dry, clean, free of dirt, oil, grease and all other foreign matter. The age of new concrete must be at least 28 days and a minimum tensile strength of 200 psi is required of the prepared surface before coating. Mechanical methods such as sandblasting, scarifying or shot blasting should be carried out to remove the weak layer of surface laitance. Acid etching is possible but less desirable. Care must be taken to ensure all residue acid must be removed with clean water before priming.

EXISTING CONCRETE: The surface must be existing structurally sound, dry and free of all contaminants. Weak or contaminated concrete must be removed until sound concrete is realized. Old coatings, toppings, waxes, oils etc. must be removed by mechanical methods or acid etching before priming. Acid etching is possible but less desirable.

Priming

Apply by roller one coat of Epoxy Penetrating Primer. Allow to become dry overnight before applying Cemseal E100SL solventless epoxy floor coating.

Mixing

First pour the liquid Component A into a suitable container and stir with a slow speed paddle stirrer. Slowly, add Component B until a consistent colour is achieved.

Application

Apply the mixed Cemseal E100SL compound onto the prepared floor and an intermittent period of 8 hours should be allowed prior to the subsequent coats. Cemseal E100SL epoxy resin coating can be applied either by roller, sprayer or brush.

Limitation

Do not apply over moisture, in damp or wet concrete or rising dampness conditions. Do not thin with solvents.

The application of Cemseal E100SL is not possible at below 15°C and on frozen surface.

For Further	Cemseal Industries Sdn Bhd (Company No. 884153-T)
Information	No. 9 & 11, Jalan Besi, Taman Sri Putri, 81300 Skudai, Johor, West Malaysia. Tel : 607-558 3320, Fax : 607-556 9127, E-mail : info@cemseal.com.my
First Aid	In case of contact with eyes, skin or body wash immediately with clean fresh water or stand under shower and wash off. In case of inhaling of vapor or ingestion
	remove to fresh air and do not induce vomiting. Obtain immediate medical treatment.
Statement of	The technical information and application advice given in this Cemseal publication are based on the present state of our best scientific and practical knowledge.
Responsibility	As the information herein is of a general nature no assumption can be made as to a products suitability for a particular use or application and no warranty as to its
	accuracy, reliability or completeness either expressed or implied is given other than those required by law. The user, is responsible for checking the suitability of
	products for their intended use.
Note	Field service where provided, does not constitute supervisory responsibility. Suggestions made by Cemseal either orally or in writing may be followed, modified
	or rejected by the owner, engineer or contractor since they, and not Cemseal are responsible for carrying out procedures appropriate to a specific application.